

### SMALL AND SIMPLE...

- 2000W continuous / 4000W peak power
- LCD display - Volt/Watt/Battery Level
- Ultra silent (thermal fan)
- 2 x standard North American AC outlets
- 2 x USB charging ports 2.1A (shared)
- Tablet charging compatible from USB ports
- ON / OFF Remote Control (optional)

### WORKS WITH...

- Power Tools
- Televisions
- Gaming Consoles
- Home Electronics
- Home Appliances
- Microwaves
- and more...

## EN2000

2000W Power Inverter - Get power on the GO!  
This heavy duty Power Inverter connects directly to a 12 Volt DC battery to power microwaves, power tools, televisions, gaming consoles, home electronics and home appliances in your vehicle. This unit also features an LCD display, which shows the output wattage or input voltage and battery level. With this inverter, you will never be left without power when you need it!



Conforms to / Conforme à UL std. 458,  
Certified to / Homologué à  
CSA std. C22.2 No. 107.1



**Before Using Your Power Inverter:**  
Please read all instructions and cautionary markings on the package and manual

### Product Detail:

**Designation:** 2000 Watt POWER INVERTER

**Model:** EN2000

**Color:** Black

**AC output voltage:** 120VAC/60Hz

**Continuous AC output power:** 2000W

**Peak output power:** 4000W

**AC output wave form:** Modified sine wave

**AC output frequency:** 60 ± 3Hz

**2 x USB DC output current:** 2.1 Amp (Shared)

**Typical Weight (lbs):** 5.53 lbs

**Dimensions (in):** 2.72(H) x 14.92(L) x 5.59(W)

#### **Important Notice**

This datasheet contains information specific to products manufactured at the time of its publication  
**Contents herein do not constitute a warranty**  
©Energizer / All Rights Reserved