

SMALL AND SIMPLE...

- 3000W (15 min) / 2800W continuous / 6000W peak power
- LCD display - Volt/Watt/Battery Level
- Ultra silent (thermal fan)
- 4 x standard North American AC outlets
- 4 x USB charging ports 2.1A (shared)
- Tablet charging compatible from USB ports
- ON / OFF Remote Control (optional)

WORKS WITH...

- Power Tools
- Televisions
- Gaming Consoles
- Home Electronics
- Home Appliances
- Microwaves
- and more...

EN3000

3000W Power Inverter - Get power on the GO!
This heavy duty Power Inverter connects directly to a 12 Volt DC battery to power microwaves, power tools, televisions, gaming consoles, home electronics and home appliances in your vehicle. This unit also features an LCD display, which shows the output wattage or input voltage and battery level. With this inverter, you will never be left without power when you need it!



Conforms to / Conforme à UL std. 458,
Certified to / Homologué à
CSA std. C22.2 No. 107.1



Before Using Your Power Inverter:
Please read all instructions and cautionary markings on the package and manual

Product Detail:

Designation: 3000 Watt POWER INVERTER

Model: EN3000

Color: Black

AC output voltage: 120VAC/60Hz

AC output power: 3000W (15 min) / 2800W continuous

Peak output power: 6000W

AC output wave form: Modified sine wave

AC output frequency: 60 ± 3Hz

4 x USB DC output current: 2.1 Amp (Shared)

Typical Weight (lbs): 7.58 lbs

Dimensions (in): 4.88(H) x 13.19(L) x 5.67(W)

Important Notice

This datasheet contains information specific to products manufactured at the time of its publication
Contents herein do not constitute a warranty
©Energizer / All Rights Reserved